


MT-92A

UHF Analog Interlinking Transmitter

FEATURES

- 9.5-inch half-rack metal chassis compliant with EIA standards, easily integrates into various audio systems.
- Works with ACT analog receivers or modules to convert signals from microphones, instruments, and audio devices into UHF wireless transmission.
- Provides 16 preset channels for simple operation.
- Switchable HIGH/LOW RF power output up to 500 mW supports long-distance transmission needs.
- +48 V phantom power supports condenser microphones and professional audio equipment.
- XLR / 6.3 mm combo input with MIC/LINE sensitivity switch and adjustable gain control knob.
- Compatible with MIPRO UHF antennas and power amplifiers for extended transmission range and coverage.



SPECIFICATIONS

Chassis	Half-rack (9.5") metal chassis
Display	AF input meters, High / Low RF power, channel number
Control Interface	Channel selection button, phantom power on/off, RF power output switch
Frequency Range	UHF 506–934 MHz (country dependent)
Channels	16 preset channels
Modulation Type	FM modulation
RF Power Output	LOW: < 100 mW, HIGH: < 500 mW (country dependent)
Audio Control	Gain, Sensitivity (MIC / LINE)
Phantom Power	+48V
Audio Input	XLR / 6.3 mm TRS combo socket
Antenna	50 Ω TNC female
Power Supply	DC 12–15 V. External AC 100–240 V switching power supply
Dimensions	210 × 44 × 206 mm (W × H × D)
Weight	Approx. 1.1 kg