

# MT-58 5 GHz Digital Transmitter

## Features

- The MT-58 is a digital transmitter with a rotatable 3.5 mm phone jack for easy fitting to a musical instrument, PC or projector with a built-in pickup.
- The compact MT-58 can be snugly attached to the instruments with various instrument holders and is easy to install and remove. It can pair with an MR-58 digital pedal receiver to get rid of the problem of tangled cables for carefree performances with truly wireless transmission.
- Operates in ISM 5 GHz frequency band and eliminates the interference from 2.4 GHz telecommunication products as well as the UHF band, which has more and more severe interference and strict telecom regulations, thus the MT-58 has excellent performance especially for instrument signals. Its digital circuitry design eliminates the distortion caused by the analog system, so the natural sound of the musical instruments can be reproduced.



## Specifications

Frequency Band	ISM 5.8 GHz
RF Power Output	20 mW (country dependent)
Max. Audio Input	6.5 dBV
Battery Meter	4-level green/red LED display
Impedance	Approx. 1 M $\Omega$
Connector	3.5 mm. Another 3.5 mm to 6.3 mm threaded adapter is included.
Battery Type	One 18500 Li-ion battery
Battery Charging	MP-24 charging station
Dimensions	35 × 84 × 29 mm (W × H × D)
Weight	Approx. 61 g