

ACT-700T

UHF Analog Wideband Bodypack Transmitter

FEATURES

- MIPRO's wideband analog bodypack transmitter is designed for use with the ACT-700 Series receivers, offering reliable performance for professional applications.
- Compact and lightweight housing with a streamlined design ensures secure and comfortable belt-worn use.
- A backlit LCD clearly displays group, channel, battery level, and operational menus.
- Supports essential settings including mute mode, input sensitivity adjustment, RF output power, and lock.
- Offers both onboard mute switch and external mute control for flexible operation.
- Features a MIPRO 4-Pin Mini XLR input compatible with MIPRO's full range of lavalier and headworn microphones, as well as instrument microphones.
- Five-stage input gain adjustment allows optimal input level control for clear, distortion-free audio.
- Incorporates MIPRO's exclusive ACT™ function for fast and accurate frequency synchronization.
- Patented dual-purpose battery compartment allows quick switching between AA and rechargeable Li-ion batteries.
- Built-in USB Type-C charging port and charging contacts with foolproof protection circuitry support cable and drop-in charging.
- Detachable metal belt clip allows upright or inverted mounting for secure and convenient wearing.



SPECIFICATIONS

Frequency Range	UHF 480–934 MHz (country dependent)
Bandwidth	72 MHz
Display	Backlit LCD displays channel, battery status and menus
Control Interface	ACT sync sensor, setting buttons and mute button
Mic. Capsule Modules	MIPRO lavalier and headworn mics
Input Connector	MIPRO 4-Pin Mini XLR
Audio Control	AF Gain
Max. Audio Input	0 dBV
Gain Setting	-12 dB to +12 dB / 6 dB per segment
RF Power Output	10 mW / 50 mW switchable (country dependent)
Power Supply	One 18500 Li-ion battery or two AA alkaline
Battery Charging	MP-800 / MP-820 charging dock or USB Type-C
Dimensions	63 × 80 × 25 mm (W × H × D)
Weight	Approx. 97 g

