


AD-808

UHF 4-Channel Transmitting Antenna Combiner

FEATURES

- Integrates up to four UHF-band MI-909T transmitters into a single antenna output, simplifying antenna setup.
- Built-in high-linearity broadband amplifier reduces intermodulation distortion and signal loss, enhancing audio stability and transmission range.
- Minimizes interference and complexity from multiple antenna setups, ideal for professional stage and monitoring applications.
- LED indicators on the front panel light up when input power reaches the specified level, allowing real-time status monitoring.



SPECIFICATIONS

Frequency Range	UHF 470 – 960 MHz
Gain	0 dB ± 2 dB
Max. RF Input Power	20 dBm (100 mW)
Intermodulation Distortion	< -57 dBc
System Impedance	50 Ω
Input Connectors	TNC × 4
Output Connectors	TNC × 1
Power Supply	DC 12 – 15 V, AC 100 – 240 V
Dimensions	210 × 44 × 204 mm (W × H × D)
Weight	Approx. 1.1 kg