

MJ-53

Condenser Microphone Adapter

FEATURES

- Converts MIPRO 4-pin Mini XLR condenser microphones to standard XLR inputs.
- Supports 12 – 48 V phantom power supply.
- Incorporates an electronically balanced amplifier circuit with approximately 200 Ω output, delivering high signal-to-noise ratio and wide dynamic range.
- Provides a broad frequency response of 50 Hz – 20 kHz, ensuring stable and clear long-distance transmission.
- Durable full-metal housing with belt clip for convenient professional use.

SPECIFICATIONS

Frequency Response	50 Hz – 20 kHz
Output Impedance	200 Ω (Balanced)
Max Output Voltage	2.52 V @ 1 kHz, THD 1%
Dynamic Range	120 dBA
Input Jack	MIPRO 4-pin Mini XLR
Output Jack	XLR
Power	12 – 48 V phantom power. Current Drain: 2.0 mA
Dimensions	19 x 90 mm (\varnothing x L)
Weight	Approx. 67 g

