

# MRM-58

## 5 GHz Digital Receiver Module

### FEATURES

- Operates on the ISM 5.8 GHz band with 12 preset channels, supporting 8 selectable IDs plus 1 special ID per channel, providing greater bandwidth and reduced interference.
- Includes auto-scan and ACT synchronization functions for quick and intuitive frequency setup.
- Employs true diversity reception technology to ensure highly stable wireless audio transmission.
- LED indicators clearly show channel, RF and AF signal strength.
- Modular design allows direct installation in MIPRO portable PA systems for efficient setup and servicing.



### SPECIFICATIONS

Frequency Range	ISM 5.8 GHz
Channels	12 preset channels with 8 selectable IDs and one specific ID
Display	LED numeric channel, RF indicator and AF levels
Channel Setting	Manually set up the desired channel or scan for an open channel
Frequency Synchronization	ACT sync
Receiving Mode	True diversity
S/N Ratio	> 113 dBA
Frequency Response	20 Hz – 20 kHz
Compatible Models	MIPRO MA Series
Dimensions	75 × 35 × 147 mm (W × H × D)
Weight	Approx. 80 g