

MPB-58

5 GHz Antenna Booster

FEATURES

- Designed for the 5 GHz frequency band, delivering a fixed gain of approximately 20 dB to offset signal loss from long cable runs.
- Powered via bias voltage from the receiver's antenna port and supports external antenna connections for versatile deployment.
- Aluminum alloy housing ensures superior heat dissipation and waterproof performance, enhancing system reliability.

SPECIFICATIONS

| | |
|------------------|-----------------------------------|
| Frequency Range | ISM 5.8 GHz |
| Gain | Approx. 20 dB (Fixed) |
| Input Connector | 1 × TNC |
| Output Connector | 1 × TNC |
| System Impedance | 50 Ω |
| Power Supply | DC 12 – 24 V |
| Power Output | DC 12 – 24 V (equals to the bias) |
| Dimensions | 41 × 80 × 24 mm (W × H × D) |
| Weight | Approx. 260 g |

