



MI-580R

5 GHz Digital Stereo Bodypack Receiver

FEATURES

- Ultra-compact reinforced polymer housing for durability and portability.
- Operates in the ISM 5 GHz band for superior interference resistance and stable, high-quality audio reception.
- True diversity reception technology enhances signal reliability.
- Supports STEREO and MIXED monitoring modes for flexible use.
- 4-band EQ for tailored tonal adjustments.
- Outstanding stereo separation (>100 dB) for immersive and detailed sound.
- 3.5 mm stereo earphone jack compatible with MIPRO professional monitoring earphones and most commercial models.
- Patented battery compartment accommodates AA or Li-ion batteries, with USB Type-C charging, safety protection, and no need for a dedicated charging dock.



SPECIFICATIONS

Housing	Reinforced plastic
Display	Backlit graphic LCD
Control Interface	ACT sync sensor, setting buttons and volume control
Frequency Range	ISM 5.8 GHz
Receiving Mode	True diversity
Audio Mode	STEREO / MIXED
L / R Balance Adjustment	Allows shifting the stereo output toward the left or right channel.
ENG Mode	Yes, up to 16 sets (requires transmitter setup)
EQ	FLAT / LO-CUT / LO-BOT / HI-BOT
Frequency Response	20 Hz – 23 kHz (stereo)
Dynamic Range	≥ 109 dBA (system)
Stereo Separation	> 100 dB
THD	< 0.1% @ 1 kHz
Latency	Approx. 1.8 ms (group B)
Sensitivity	5 μV (S/N > 100 dB)
Output Power	Left/Right × 100 mW @ 16 Ω
Earphone Jack	3.5 mm TRS
Power Supply	One 18500 Li-ion battery or two AA alkaline
Battery Charging	USB Type-C
Operating Time	> 8 hours
Accessories	E-9 / E-8S (optional)
Dimensions	63 × 95 × 25 mm (W × H × D)
Weight	Approx. 160 g