## MPB-58 5 GHz Antenna Booster

## **Features**

- It is optimized in the ISM 5 GHz band to amplify the antenna signal, offering 20 dB gain to compensate for signal loss over long antenna cables and to increase the reception range and signal stability.
- The antenna booster can be powered by the bias of the receiver's antenna connector or by an external power supply, allowing longer antenna cables can be connected with more boosters.
- With an aluminum casing, it features superb heat dissipation and is waterproof.





## **Specifications**

| Frequency Band         | 5.8 GHz   |
|------------------------|---|
| Gain                   | Fixed, approx. 20 dB  |
| Input Connector        | 1 × TNC   |
| Output Connector       | 1 × TNC   |
| System Impedance       | 50 Ω  |
| Input Power            | DC 10 – 24 V  |
| Regulated Power Output | Equals to the bias  |
| Dimensions             | 41 × 80 × 24 mm (W × H × D)   |
| Weight                 | Approx. 260 g   |
| Note                   | Refer to the actual product in the event of product description discrepancy |

