

E-5S Single-side Earphone

Features

- For MTG-100R / MTG-100Ra digital receivers.



Specifications

| | |
|--------------------|---|
| Driver Unit | 24 Ø |
| Frequency Response | 100 Hz – 20 kHz |
| Sensitivity | 108 dB ± 3 dB @ 1 mW |
| Max. Input Power | 100 mW |
| Impedance | 32 ± 15% Ω @ 1 kHz 1 mW |
| Cable Length | 120 cm |
| Connector | 3.5 mm TRS |
| Weight | Approx. 14 g |
| Note | Refer to the actual product in the event of product description discrepancy |