


# MT-92A UHF Analog Interlinking Transmitter

## Features

- Transmits the output signals of microphones, instruments and other audio equipment.
- Presets 16 channels.
- The maximum power output is up to 500 mW.
- Supplies 48 V phantom power for condenser microphones.
- Pairs with the ACT series analog receivers for long-distance wireless transmission.



## Specifications

Frequency Range	UHF 506 – 934 MHz (country dependent)
Modulation Type	FM modulation
Receiver	ACT series analog receivers
RF Power Output	Low < 100 mW, High < 500 mW (country dependent)
Phantom Power	48 V
Audio Input	XLR / 6.3 mm TRS combo socket
Power Supply	DC 12 – 15 V, AC 100 – 240 V
Dimensions	210 × 44 × 206 mm (W × H × D)
Weight	Approx. 1.1 kg