

ACT-600T

UHF Digital Bodypack Transmitter

FEATURES

- Designed for seamless compatibility with ACT-600 Series digital receivers.
- Lightweight, streamlined housing with patented design for practical and comfortable belt-worn use.
- Backlit LCD display and intuitive buttons clearly show channel, battery status, and AF level.
- Supports comprehensive settings including mute mode, sensitivity, low-cut filter, audio limiter, RF power, input polarity, and key lock.
- Provides both on-unit mute control and external mute connection for flexible operation.
- MIPRO 4-pin Mini XLR input supports MIPRO lavalier, headset microphones, and instrument cables.
- Six-step gain control allows precise input level adjustment for improved audio quality.
- Built-in MIPRO ACT™ technology enables fast and accurate frequency synchronization.
- Patented dual-purpose battery compartment supports AA or rechargeable Li-ion batteries.
- Integrated USB Type-C charging and charging contacts with foolproof protection circuitry support cable and dock charging.
- Adjustable metal belt clip ensures secure wearing and convenient operation.

SPECIFICATIONS

Frequency Range	UHF 480–934 MHz (country dependent)
Bandwidth	48 MHz
Display	Backlit LCD displays channel, battery status, AF meters and menus
Control Interface	ACT sync sensor, setting buttons and mute button
Encryption	256-bit Digital Encryption
Mic. Capsule Modules	MIPRO lavalier and headworn mics
Input Connector	MIPRO 4-Pin Mini XLR
Audio Control	AF Gain, Low Cut, AF Limiter and Input Polarity
Max. Audio Input	0 dBV
Gain Setting	-12 dB to +18 dB / 6 dB per segment
RF Power Output	10 mW / 50 mW switchable (country dependent)
Power Supply	One 18500 Li-ion battery or two AA alkaline
Battery Charging	MP-800 / MP-820 charging dock or USB Type-C
Dimensions	63 × 80 × 25 mm (W × H × D)
Weight	Approx. 96 g

