


ACT-58T

5 GHz Digital Bodypack Transmitter

FEATURES

- MIPRO's digital bodypack transmitter operating in the 5 GHz ISM band is designed for use with MIPRO 5 GHz receivers and wireless PA systems, suitable for small-scale performances and conferencing applications.
- Compact and sleek housing provides secure and comfortable wearing.
- Three-stage battery status indicator and audio status LED provide clear power and mute status monitoring.
- Offers both onboard mute switch and external mute control for flexible operation.
- Features a MIPRO 4-Pin Mini XLR input compatible with MIPRO's full range of lavalier and headworn microphones, as well as instrument microphones.
- Wide dynamic range audio input supports high and low impedance sources and prevents signal overload and distortion.
- Incorporates MIPRO's exclusive ACT™ function for fast and accurate frequency synchronization.
- A simple battery compartment holds two AA batteries for quick and convenient replacement.



SPECIFICATIONS

Frequency Range	ISM 5.8 GHz
Bandwidth	125 MHz
Display	Three-segment LED battery indicator and mute indicator
Control Interface	ACT sync sensor and mute button
Mic. Capsule Modules	MIPRO lavalier and headworn mics
Input Connector	MIPRO 4-Pin Mini XLR
Max. Audio Input	6.5 dBV
RF Power Output	20 mW (country dependent)
Power Supply	Two AA alkaline
Dimensions	63 × 82 × 22 mm (W × H × D)
Weight	Approx. 72 g