

MT-58

5 GHz Digital Transmitter

FEATURES

- Integrated 3.5 mm plug with 0°–90° adjustable rotation and included 6.3 mm adapter for compatibility with electric guitars, basses, keyboards, and other instruments.
- Operates in the ISM 5 GHz band, avoiding congested 2.4 GHz and UHF frequencies for low-latency, interference-free performance.
- MIPRO patented uncompressed digital audio technology ensures full tonal integrity and dynamic range.
- Works seamlessly with MIPRO wireless receivers or PA systems with built-in receivers, as well as laptops, tablets, and other audio devices.
- Powered by a rechargeable 18500 lithium-ion battery for long-lasting performance, with dedicated charging dock for quick, convenient recharging.



SPECIFICATIONS

Frequency Range	ISM 5.8 GHz
RF Power Output	20 mW (country dependent)
Max. Audio Input	6.5 dBV
Input Impedance	Approx. 1M Ω
Input Connector	3.5 mm. Another 3.5 mm to 6.3 mm threaded adapter is included.
Display	4-level green/red LED battery level
Control Interface	ACT sync sensor
Power Supply	One 18500 Li-ion battery
Battery Charging	MP-24 charging dock
Dimensions	35 × 84 × 29 mm (W × H × D)
Weight	Approx. 61 g