

# ACT-58H

## 5 GHz Digital Handheld Transmitter

### FEATURES

- Handheld transmitter for MIPRO's 5 GHz digital series receivers and wireless PA systems, ideal for compact performances and meetings.
- Sleek and ergonomic design provides a comfortable grip and professional look.
- High-rigidity multi-layer all-metal grille with removable upper grille and internally threaded lower grille for durability, pop protection, and clear sound.
- Standard with MU-80 cardioid condenser capsule module; supports interchangeable MIPRO condenser or dynamic capsule modules.
- Upper housing includes an LED indicator showing battery status and wake-up function for clear status monitoring.
- Incorporates MIPRO's exclusive ACT™ function for quick and accurate frequency synchronization.
- Supports unique "Auto Wake-Up" feature that instantly activates the transmitter from mute standby when moved. Requires ACT-5800 Series receiver activation.
- Simplified battery compartment powered by AA batteries for convenient replacement.
- Lower housing includes a replaceable color-coded ID ring and built-in high-efficiency antenna for a clean, functional design.



### SPECIFICATIONS

Frequency Range	ISM 5.8 GHz
Bandwidth	125 MHz
Display	LED displays three-segment battery levels. A wake-up status indicator.
Control Interface	ACT sync sensor
Mic. Capsule Modules	MU-80 condenser or other compatible capsule modules
RF Power Output	20 mW (country dependent)
Power Supply	2 × AA alkaline
Dimensions	51 × 257 mm (Ø × L)
Weight	Approx. 240 g

