

# ACT-580H

## 5 GHz Digital Handheld Transmitter

### FEATURES

- Handheld transmitter designed for MIPRO's 5 GHz digital series receivers and wireless PA systems, ideal for small-scale performances and conferences.
- Ergonomic matte black metal housing provides a comfortable grip, ultra-low handling noise, and a sleek professional look.
- Patented multifunction power module integrates the power switch and LCD display for intuitive operation, showing channel, battery status, and AF level indicators.
- Fitted with MIPRO's uniquely designed capsule module—removable upper grille for cleaning and threaded lower grille for impact, rolling, and pop protection.
- Standard with MU-80A supercardioid condenser capsule module; supports interchangeable MIPRO condenser or dynamic capsule modules and compatible ones from other brands.
- Incorporates MIPRO's exclusive ACT™ function for quick and precise frequency synchronization.
- Patented dual-purpose battery compartment supports quick switching between AA and rechargeable Li-ion batteries.
- Features USB Type-C charging with foolproof protection circuitry for direct cable charging.
- Lower housing features a replaceable color-coded ID ring for channel identification. A patented antenna cover houses a high-efficiency wideband transmitting antenna.



### SPECIFICATIONS

Frequency Range	ISM 5.8 GHz
Bandwidth	125 MHz
Display	Backlit LCD displays channel, battery status and AF signal levels
Control Interface	ACT sync sensor
Mic. Capsule Modules	MU-80A condenser or other compatible capsule modules
RF Power Output	20 mW (country dependent)
Power Supply	One 18500 Li-ion battery or two AA alkaline
Battery Charging	MP-800 / MP-820 charging dock or USB Type-C
Dimensions	51 × 272 mm (Ø × L)
Weight	Approx. 320 g

