

MTG-100Ha

UHF Digital Handheld Transmitter

FEATURES

- Handheld wireless microphone design delivers clear and natural vocal reproduction.
- Backlit LCD displays battery and channel information.
- Operates in 863 – 865 MHz and 926 – 928 MHz international standard bands, compliant with regulations in most countries for license-free use.
- Equipped with channel selection, gain, and sensitivity adjustment for fine-tuned output levels.
- Mute button with enable/disable function via internal settings for flexible operation.
- Provides 16 preset channels, allowing at least three systems to operate simultaneously without interference.
- Compatible with MTG-100R / MTG-100Ra receivers.

SPECIFICATIONS

Frequency Range	863–865 MHz, 926–928 MHz (country dependent)
Channels	16 preset channels
Modulation Type	Digital modulation (encryption and interference-resistant)
RF Power Output	<10 mW (High / Mid / Low switchable)
Display	Backlit LCD
Control Interface	MODE / SET buttons, mute button
Mic. Capsule Modules	MU-80 condenser or other compatible capsule modules
Gain Setting	-12 to +9 dB / 3 dB per segment
Power Supply	2 AA alkaline
Dimensions	51 × 258 mm (Ø × L)
Weight	Approx. 260 g

