

ACT-580H

5 GHz Digital Handheld Transmitter

FEATURES

- Handheld transmitter designed for MIPRO's 5 GHz digital series receivers and wireless PA systems, ideal for small-scale performances and conferences.
- Ergonomic matte black metal housing provides a comfortable grip, ultra-low handling noise, and a sleek professional look.
- Patented multifunction power module integrates the power switch and LCD display for intuitive operation, showing channel, battery status, and AF level indicators.
- Fitted with MIPRO's uniquely designed capsule module—removable upper grille for cleaning and threaded lower grille for impact, rolling, and pop protection.
- Standard with MU-80A cardioid condenser capsule module; supports interchangeable MIPRO condenser or dynamic capsule modules and compatible ones from other brands.
- Incorporates MIPRO's exclusive ACT™ function for quick and precise frequency synchronization.
- Patented dual-purpose battery compartment supports quick switching between AA and rechargeable Li-ion batteries.
- Features USB Type-C charging with foolproof protection circuitry for direct cable charging.
- Lower housing features a replaceable color-coded ID ring for channel identification. A patented antenna cover houses a high-efficiency wideband transmitting antenna.



SPECIFICATIONS

Frequency Range	ISM 5.8 GHz
Bandwidth	125 MHz
Display	Backlit LCD displays channel, battery status and AF signal levels
Control Interface	ACT sync sensor
Mic. Capsule Modules	MU-80A condenser or other compatible capsule modules
RF Power Output	20 mW (country dependent)
Power Supply	One 18500 Li-ion battery or two AA alkaline
Battery Charging	MP-800 / MP-820 charging dock or USB Type-C
Dimensions	51 × 272 mm (Ø × L)
Weight	Approx. 320 g

